

Name .....

Duration: 30 mins

### Exam

#### 1- Multiple choice questionnaire (MCQ) (10 points)

Check the right answer


##### Exercise 1 :

A DC motor operates at constant flux. At nominal point:  $T_{em} = 40 \text{ Nm}$ ;  $U = 240 \text{ V}$ ;  $I = 16 \text{ A}$ . The armature has a resistance  $R$  ( $R = 0.70 \Omega$ ). What must be the voltage  $U_d$  across the armature to obtain a starting torque of moment  $T_{emd} = 80 \text{ Nm}$ ?

<input type="checkbox"/>	$U_d = 23.4 \text{ V}$	<input type="checkbox"/>	$U_d = 21.4 \text{ V}$	<input type="checkbox"/>	$U_d = 22.4 \text{ V}$
--------------------------	------------------------	--------------------------	------------------------	--------------------------	------------------------

##### Exercise 2:

On the rod of a cylinder is placed a mass of 3000kg, the cylinder bore of the cylinder is 80mm.



Calculate

1- The pressing force exerted on the oil?

<input type="checkbox"/>	$F = 300 \text{ N}$	<input type="checkbox"/>	$F = 30000 \text{ N}$	<input type="checkbox"/>	$F = 3000 \text{ N}$
--------------------------	---------------------	--------------------------	-----------------------	--------------------------	----------------------

2- The pressed surface?

<input type="checkbox"/>	$S = 50 \text{ cm}^2$	<input type="checkbox"/>	$S = 5 \text{ cm}^2$	<input type="checkbox"/>	$S = 0.5 \text{ cm}^2$
--------------------------	-----------------------	--------------------------	----------------------	--------------------------	------------------------

3- The pressure in bar?

<input type="checkbox"/>	$p = 6 \text{ bar}$	<input type="checkbox"/>	$p = 600 \text{ bar}$	<input type="checkbox"/>	$p = 60 \text{ bar}$
--------------------------	---------------------	--------------------------	-----------------------	--------------------------	----------------------

##### Exercise 3:

A permanent magnet stepper motor having the following features:

Stator: 8 phases; Rotor: 24 poles; Switching: Symmetrical; Angular pitch:  $3^\circ,75$

1/ Calculate the number of steps per turn.

<input type="checkbox"/>	$N_{p/tr} = 95$	<input type="checkbox"/>	$N_{p/tr} = 96$	<input type="checkbox"/>	$N_{p/tr} = 90$
--------------------------	-----------------	--------------------------	-----------------	--------------------------	-----------------

2/ Determine the type of switching.

<input type="checkbox"/>	$K1 = 1$	<input type="checkbox"/>	$K1 = 3$	<input type="checkbox"/>	$K1 = 2$
--------------------------	----------	--------------------------	----------	--------------------------	----------

3°/ Determine the number of steps  $N_p$  to be made for the rotor to rotate by  $375^\circ$ .

<input type="checkbox"/>	$N_p = 80$	<input type="checkbox"/>	$N_p = 60$	<input type="checkbox"/>	$N_p = 100$
--------------------------	------------	--------------------------	------------	--------------------------	-------------

4/ Knowing that the motor takes 100 steps/s.

4-1 Determine the frequency  $f$  of the stepper motor control circuit clock signal.

<input type="checkbox"/>	$f = 50 \text{ Hz}$	<input type="checkbox"/>	$f = 100 \text{ Hz}$	<input type="checkbox"/>	$f = 500 \text{ Hz}$
--------------------------	---------------------	--------------------------	----------------------	--------------------------	----------------------

4-2 Calculate the time  $t$  in (s) set for the rotor to describe an angle of  $3000^\circ$ .

<input type="checkbox"/>	$t = 10 \text{ s}$	<input type="checkbox"/>	$t = 8 \text{ s}$	<input type="checkbox"/>	$t = 9 \text{ s}$
--------------------------	--------------------	--------------------------	-------------------	--------------------------	-------------------

4-3 Calculate the engine speed  $n$  in **rpm**.

<input type="checkbox"/>	$n = 62,5$	<input type="checkbox"/>	$n = 64,5$	<input type="checkbox"/>	$n = 62$
--------------------------	------------	--------------------------	------------	--------------------------	----------

**2- QUESTIONS (10 points)**

**Answer with true or false? and correct the errors?**

1. The distributor is associated with an electric motor, the contactor is the pre-actuator associated with a pneumatic cylinder. (            )  
.....
2. Pre Actuators are elements that, in response to control signals, facilitate the distribution of power energy to the actuators. (            )  
.....
3. The double rod cylinder has a rod passing through the entire body and a piston placed in the middle. (            )  
.....
4. Variable reluctance stepper motor: This motor features teeth with identical pitch on both the stator and rotor; the rotor itself is not magnetized. (            )  
.....
5. A bistable dispenser if the return of the drawer to its initial position is ensured by a return spring. (            )  
.....
6. An electromagnetic relay comprises a coil powered by the control circuit, and its mobile core induces the switching of contacts that can be positioned within a power circuit. Electromagnetic relays are typically employed for low-power applications. (            )  
.....
7. Single Acting Cylinder: the extension and retraction of the rod is carried out by the application of pressure. (            )  
.....
8. Supply voltage of an electromagnetic relay: It is an alternating voltage which excites the coil. (            )  
.....
9. A stepper motor converts control pulses into a rotational movement of the rotor, typically characterized by **n** steps. (            )  
.....
10. The disconnecter is a connecting device designed to isolate a circuit for performing maintenance or modification operations on the electrical circuits located upstream. (            )  
.....